



# CARL MARTIN

## OCTASWITCH MK3

LOOP SWITCHER

### SPECIFICATIONS

- **Input:** 500K Ohm (buffer)
- **Output:** 560K Ohm (buffer)
- **S/N Ratio:** 70 dB
- **Loops:** 8 pcs. true bypass relay
- **Presets:** 8 pcs via DIP switch
- **External Switch:** 2 pcs (latching)
- **Power consumption:** max. 380 mA
- **Power supply:** 9 V DC (regulated), 500 mA minimum, 2.1 mm female plug, center negative (-)

A flexible loop switcher with 8 loops and up to 32 presets, ideal for complex pedalboard setups and MIDI integration.

### KEY FEATURES

- **Programmable loop switcher with 8 loops**
- **True bypass with buffer option**
- **MIDI-compatible external switching**
- **Store up to 32 presets**
- **Solid metal construction**



- **Dimensions:** 311 x 155 x 65 / 12.24" x 6.10" x 2.56"
- **Weight:** 1.6 kg / 3.53 lbs
- **SKU:** CM-OSMK3
- **EAN:** 852940000622

# CARL MARTIN

Carl Martin / Dan Music Partner, Rugvaenget 1  
DK-8500 Grenaa, Denmark, [info@carlmartin.com](mailto:info@carlmartin.com)